




## PLU 2

### *Powerful, autonomous, portable lighting unit*

It is not possible to list all the possible uses of Teklite Portable Lighting Units. The powerful floodlighting which it gives can be used for maintenance or inspections in dark places, for emergency lighting or as lighting for Police, Fire Services or night breakdown services of all kinds. The Teklite PLU 2 is self-contained and draws its energy from a sealed maintenance-free battery.



**MOBILE, PORTABLE & EMERGENCY LIGHTING**

# Specifications

## Technical details



70 Watt, 12 Volt HPS (High Pressure Sodium) or MH (Metal Halide) bulb.  
Lamp protection : IP65



Rigid carrying handle.



Built-in circuit board with integrated ON/OFF switch.



Binder socket to plug in the Teklite charger to charge the 12 volt 12 Ah battery.  
Finish : Yellow RAL 1007  
Red RAL 3000



Lamp in closed position gives protection against accidental damage.



Strong rubber caps for good stability.

## PLU 2 models

Model	Cat. No.	Endurance	Weight	Amps	Lumens
PLU 2 HPS (70W-12V HP Sodium)	15525	75 min.	9,0 kg	7,0	6500
PLU 2 MH (70W-12V Metal Halide)	15526	75 min.	9,0 kg	7,0	5000

# Chargers

For any device powered by a rechargeable battery, the charger is as important as the device itself. The correct Teklite charger ensures a full charge and maximum battery life.

## Recommended Teklite charger for vehicle battery supply



### 12/12V Charger Module

Model 12/12V for 12 volt vehicles Cat. No. 16331

### 24/12V Charger Module (not shown)

Model 24/12V for 24 volt vehicles Cat. No. 16332

This module may be fixed anywhere in the vehicle near to where the PLU 2 is stored.

Input voltage : (Cat. No. 16331) 10,6 to 16 volt  
(Cat. No. 16332) 20 to 32 volt

Dimensions : 195(L) x 65(W) x 115(H) mm

Weight : 1,2 kg

Finish : Blue stove enamel RAL 5012

## Recommended Teklite charger for 230 volt supply



### 2 Amps Battery Charger

Model 2 Amps Battery Charger for 230 volt supply Cat. No. 15683

Model 2 Amps Battery Charger for 110 volt supply Cat. No. 36216

This is a compact charger designed for charging the PLU 2. Fuse protected on input and electronic protection for short circuit and reverse polarity on output.

Maximum charging current : 2,3 amps.

Input voltage : 220-250V 50Hz / 110-120V 60Hz

Recommended for batteries:  
12 volt- 12 Ah / Time to charge : 6 hours

Max. ambient temperature : 40°C

Controls : Mains switch

Indicators	: 'Mains ON'	Red LED
	'CHARGING'	Yellow LED
	'CHARGE COMPLETE'	Green LED

Dimensions : 207(L) x 115(W) x 165(H) mm

Weight : 3 kg

Finish : Blue stove enamel RAL 5012

**NOTE :** Chargers will not charge batteries where due to deep discharge the voltage is less than 7,5 volt.



All details given in this publication are approximate and may be subject to change without notice.

Distributor :

**CLARK MASTS TEKSAM NV**, Woudstraat 21, B-3600 Genk, Belgium

Tel : +32 (0)89 38 44 72 - Fax : +32 (0)89 38 61 41 - E-mail : info@teksam.be - Website : www.teklite.com

TEKLITE is a division of Clark Masts Teksam NV

ISO 9001:2000